

Product data sheet MBZ 300 N8 *



Smoke and heat extraction control panel for smoke and heat extraction drives with a total power consumption of 8 A

AREAS OF APPLICATION

- → Connection options for small smoke and heat extraction solutions
- → For smoke and heat extraction system drives with a total power consumption of 8 A
- → Control of electromotive 24 V drives for smoke and heat extraction in the event of a fire
- → Control of a controlled natural ventilation

MBZ 300 N8 *



PRODUCT FEATURES

- → Modular design to allow flexible adaptation to project-specific requirements
- ightarrow Convenient extension by clicking on another module in a control unit
- → Simple service and installation thanks to status display directly on the module
- → Configuration software simplifies commissioning and configuration
- ightarrow Available with pre-wired rail-mount terminal blocks for quick installation
- → Safety and reliability confirmed by VdS certification

TECHNICAL DATA

TEOHNIOAE DATA	
Productname	MBZ 300 N8 *
Dimensions	300 x 400 x 200 mm
Width	300 mm
Height	400 mm
Depth	200 mm
Material	Sheeting
Colour	grey RAL 7035
IP rating	IP30
Service temperature	-5 - 40 °C
Operating voltage	230 V AC
Power consumption (max.)	240 W
Connection cross-section / mains	2.5 mm ²
Output voltage	24 V DC +/-15%
Residual ripple	2 %
Output current (max.)	8 A
Duty rating with maximum output current	30 %
Motor cable wire size	4 mm ²
Battery capacity	7 Ah
Alarm groups	1
Vent groups	1 Stk.
Networking of several control units	connection with optional CAN Bus modules
Signal outputs available	1 status contact per CM/SM, 6 signal contacts per ERM for which parameters can be set
Parameter setting of control units	via USB interface an PC software
Standard conformity	EN 12101-10, ISO 21927-9
Approvals	VdS

MBZ 300 N8 '



VARIANTS / ORDER INFO

Designation

MBZ 300 N8 with rail-mount terminal blocks *

MBZ 300 N8 *

ACCESSORIES

FT 4 K *

SHEV button with plastic housing for the connection to GEZE control panels



Designation

FT 4 K SHEV button *

GC 401 RS + 402 WVS SET *

Rain and wind sensor set for use with the MBZ 301 control panel $\,$



GC 401 RS *

Rain sensor for use with the MBZ 301 control panel



GC 402 WVS *

Wind speed sensor for use with the MBZ 301 control panel



Product data sheet | Page 4 of 9

MBZ 300 N8 3



GC 403 WDS *

Wind direction sensor for use with the MBZ 301 control panel



LTA-24-AZ

Vent switch with control keys OPEN / CLOSE and LED function display



Designation

LTA-24-AZ vent switch

LTA-LSA *

Vent switch with rotary knob for OPEN / CLOSE



Designation

LTA-LSA vent switch *

E 71 *

Room thermostat for ventilation control



Designation

E 70 room thermostat *

Product data sheet | Page 5 of 9

MBZ 300 N8 *



RAIN AND WIND CONTROL *

Weather station and control unit for rain and wind monitoring



Designation

Rain and wind control *

RM 1003 *

Smoke detector for GEZE control panels



Designation

RM 1003 smoke detector *

WM 1006 *

Heat detector for GEZE SHEV control panels



Designation

WM 1005 heat detector *

SCT KEY SWITCH

Key switch for authorised activation and for changing the mode of operation of automatic doors



Product data sheet I Page 6 of 9

MBZ 300 N8 *



Designation

SCT key switch

SCT key switch

WRM-24 *

Receiving module for activating automatic doors and window drives with 24 V DC $\,$



Designation

WRM-24 receiving module *

WRM-24B *

Receiving module for activating automatic doors and window drives with 24 $\mbox{V\,DC}$



Designation

WRM-24B receiving module *

WTH *

Remote control for activating GEZE automatic doors and window drives via the GEZE wireless programme



Designation

WTH-2 remote control, 2 channel *

WTH-4 remote control, 4 channel *

WTH-1 remote control, 1 channel *

Product data sheet | Page 7 of 9

MBZ 300 N8 '



WTM *

Transmitting module for activating GEZE automatic doors and window drives via the GEZE wireless programme



Designation

WTM transmitting module *

FT 4 A *

SHEV button for the connection to GEZE control panels



Designation

FT 4 A SHEV button *

FT 4 A - VDS *

SHEV button with VdS approval for the connection to GEZE control panels $\,$



Designation

FT 4 A - VdS SHEV button

Product data sheet | Page 8 of 9

MBZ 300 N8 *



GC 240 RS *

Rain sensor for use with the MBZ 300 and THZ/THZ Comfort control panels $\,$



Designation

GC 240 RS rain sensor *

RAIL MOUNT TERMINAL BLOCK SET 4 MM² *

For the connection of drive supply lines with cross-section up to 4 mm²



Designation

Rail mount terminal block set 4 mm² *

MBZ 300 CONTROL CABINET LOCK *

For secure locking of the MBZ 300 ccontrol cabinets



Designation

MBZ 300 control cabinet lock *

GC 162 RWA *

Smoke detector for GEZE control panels



Designation

GC 162 RWA smoke detector *

Product data sheet I Page 9 of 9

MBZ 300 N8 '



GC 163 RWA *

Heat detector for GEZE SHEV control panels



Designation

GC 163 RWA heat detector *

FT 4 A ACOUSTIC *

SHEV button with acoustic signal for connection to GEZE SHEV control panels



Designation

SHEV button FT 4 A Acoustic, *

SHEV button FT 4 A Acoustic, *

FT 4 A SECONDARY UNIT *

SHEV button for the connection to GEZE control panels



Designation

SHEV button FT 4 A secondary unit, $\,^*$

^{*} The products designated above may vary in form, type, characteristics, function, or availability depending on the country. Please get in touch with your GEZE contact person if you have any questions.